



????? ????????	?????? ??????????
1"	????? (POPET)
?????????????????	?????????
? ????????????? (???? ? ????)	Nitrile NBR
?????? ??????????	?????? ??????????
????	????????
????????	?????????
???????????????? ?????????????	Cr3
????????? ??????????	????????????? ??? ?????????
???? ??? ?????????	???
P?????	????????????? ? ?????????? ??????????
FEMALE THREAD NPT (ANSI B.1.20.1)	??????? ? ????? ??????
?????????????	????????? ??????????
-20 / +100 °C; -4 / +212 °F	????????????? ??????, ??????????????
	???????????????

?????????????????	METRIC
ISO DN (mm)	25
????? (1/???)	Da 350 a 600
????????????? ????? (1/???)	378
????????????? ????? - ?????????? (???)	34.5
??????? ???????? - ?????????? (???)	34.5
????????? ???????? - ?????????? (???)	137.9
????????? ???????? - ?????????? (???)	100
????? (??)	21.2
????? ?????? ?????? ??? ?????????? (??)	1.6
????? ?????? ?????? ??? ?????????????? (??)	1.1

??????	METRIC
????? ??????? (A)	1"
????? ?????? +? (??)	152.9
????? (??)	105.8
????????????? ??????? (??)	57.2
??? (??)	1,12

????????????? ???????

??? ????????	Tipologia	????????????? ????????
811201001	Coupler	M/COUPLER VOF100 NPT

Spare kits

??? ????????	????????????? ????????
815700958	SPARE KIT OR NBR+BK F VOF100
815700959	SPARE KIT INTERNAL PARTS F-M VOF100

Caps

??? ????????	????????????? ????????
815405010	ALUMINUM CAP N VOF100 NATURAL